

## Quantifying soil ice content with a heat pulse probe for an entire range of temperature during soil freezing and thawing

\*Yuki Kojima<sup>1</sup>, Joshua L. Heitman<sup>2</sup>, Robert Horton<sup>3</sup>

1.The University of Tokyo, 2.North Carolina State University, 3.Iowa State University

Soil freezing and thawing is important for winter hydrology. Despite its importance, measuring in-situ soil ice content  $\theta_I$  has been difficult. Volumetric heat capacity measurement with a heat pulse probe (HPP) has been used to quantify  $\theta_I$  (hereafter, VHC method). The VHC method determines  $\theta_I$  only when soil temperature is below  $-5^\circ\text{C}$ . In this study, we propose a new method to determine  $\theta_I$  from HPP by considering sensible heat balance in soils (hereafter, SHB method). We tested both VHC and SHB methods for  $\theta_I$  determination.

A HPP measures soil temperature  $T$ , volumetric heat capacity  $C$ , and thermal conductivity  $\lambda$ . For the VHC method, only  $C$  is used to determine  $\theta_I$ . For the SHB method, a HPP is inserted into soil such that each needle is located at a different depth. When the heat balance of a thin soil layer which has boundaries at the middle of each HPP needle is considered, there is conductive heat flux at the first boundary  $H_1$ , conductive heat flux at the second boundary  $H_2$ , change in sensible heat storage  $\Delta S$ , and latent heat flux  $L$ , *i.e.*,  $H_1 - H_2 - \Delta S = L$ .  $H_1$ ,  $H_2$  and  $\Delta S$  can be estimated from HPP measurements and equations, thus,  $L$  can be calculated. When  $T$  is  $< 0^\circ\text{C}$ ,  $L$  is associated with soil freezing and thawing. Thus, change in  $\theta_I$  can be determined by dividing  $L$  by latent heat for water freezing  $L_f$ .  $\theta_I$  can be determined by integrating  $\Delta\theta_I$  with respect to time once  $T$  drops below  $0^\circ\text{C}$ .

Soil was packed into  $0.3\text{ m}$  long PVC columns with  $0.28\text{ m}^3\text{ m}^{-3}$  water content. A HPP was inserted through the column wall. Additional columns were prepared for destructive sampling to determine total soil water content after soil freezing. Upper boundary temperature was initially  $5^\circ\text{C}$ , and then it was decreased to  $-15^\circ\text{C}$  gradually within 24 hours. After 6 days, the temperature was increased to  $5^\circ\text{C}$  within 24 hours. The temperature for the lower boundary was maintained at  $5^\circ\text{C}$ . Transient  $\theta_I$  was estimated with VHC and SHB methods.

$\theta_I$  determined by sampling was around  $0.20\text{ m}^3\text{ m}^{-3}$ .  $\theta_I$  estimated with the VHC method was close to  $0.20\text{ m}^3\text{ m}^{-3}$  when  $T$  was  $< -5^\circ\text{C}$ . The SHB method could additionally estimate transient  $\theta_I$  when  $T$  was between  $0$  and  $-5^\circ\text{C}$  but failed at  $T < -5^\circ\text{C}$ . Thus, we measured  $\theta_I$  for a whole  $T$  range by using the SHB method with  $T$  between  $0$  and  $-5^\circ\text{C}$  and using the VHC method with  $T < -5^\circ\text{C}$ .

A combination of SHB and VHC methods allowed determination of transient  $\theta_I$  for the entire range of temperature during freezing. Accordingly, a HPP can be a useful sensor for monitoring  $\theta_I$  under freezing and thawing conditions.